

# RCP14 Plug-in socket dimmer

230 V



The RCP14 plug-in socket dimmer can be used to control and dim lighting of up to 250 W.

It can be operated using Easywave radio transmitters with a 1-button operation or 2-button operation or by using the dimmer switch directly.

Ohmic, capacitive and inductive loads can be dimmed. This also includes dimmable energy saving lamps (ESL) and dimmable LEDs.




RCP14E5001-01-01K

## Technical specifications

Coding	Easywave Up to 32 transmitters can be programmed.
Frequency	868.30 MHz
Channels	1
Power supply	230 V AC, 50 Hz (protective contact plug)
Power consumption	0.7 W standby
Operating modes	dim with memory (2- and 1-button operation) dim without memory (2- and 1-button operation) control fixed brightness levels (2- and 1-button operation)
Output	1 electronic switch
Maximum contact load	
- resistive load	250 W
- inductive load	20 - 250 VA
- LED + ESL	7 - 100 VA
- capacitive load	250 VA
Operating temperature	-20 °C to +35 °C
Dimensions (W/L/H)	50/120/75 mm
Color	white similar RAL 9003

## Plug system



D/A/NL/S/N

## Scope of delivery

- Plug-in socket dimmer
- Operating manual

## Models

Product number	Description
RCP14E5001-01-01K	Plug-in socket dimmer, Easywave, 230V, D/A/NL/S/N, white